

INSTALLATION MANUAL

7820

ecostrip

90 CRI


24V DC | SMD 2216 | 70LEDs/m | 4,8W/m | IP20

 Requires 24V DC driver.
 Supplied in 5m roll with
 double face adhesive tape.

Cut every 10cm (7-LED segment)


one
 LIGHT

A. CUT:

The LED strip can be cut every 10cm (7-LED segment) at the clearly marked positions. Cut carefully at the desired length by using a sharp pair of scissors.

B. CONNECT:

- Use 7824 power supply cable to connect the LED strip to the LED driver's output. Ensure that the polarity is correct (red "+", black "-").
- Connect two pieces of LED strip by using the 7822 connector.

C. INSTALLATION:

Remove the 3M double face adhesive tape from the LED strip gradually during installation and fix into the required position.



Warnings:

- The mounting surface must be clean, dry and free from dust or grease.
- Make sure that the product is installed properly before connecting to electricity.
- Do not bend, fold or twist the LED strip.
- Do not bend to install in corners.
- Do not put excessive pressure on surface of LED strip.
- Do not cover LED strip with any materials.
- Do not install in ambient temperatures below -10°C or exceeding 45°C .
- Always handle the LED strip with care.
- The LED strip should not be exposed to direct sunlight.
- LED strips with different batch numbers may have slight variations in colour consistency ($\text{CCT} \pm 150\text{K}$).
- Maintenance and installation should only be carried out by a professional electrician.